



In the Claims

1-11. (Canceled)

12. (Currently Amended) An integrated satellite navigation receiver and communication device combination system, comprising:

a single portable device that includes a global positioning system (GPS) receiver part (302) and a communications transceiver part (304);

said GPS receiver part (302) including a GPS RF-receiver (308), a GPS digital processor and frequency generator (GPS-chip) (310), a GPS oscillator (oscGPS) (312), a lower-frequency oscillator (osc3) (314) operating at about 32-KHz, and a clock selector (316) for selecting between clock frequency choices for normal and time-keeping only low-power operation;

said communications transceiver part (304) including a cellphone transceiver (320), a digital signal processor (DSP) (322), a phone host CPU (324), a divider (325), and a voltage controlled oscillator (VCO) (326);

wherein, at turn-on, the GPS-chip (310) loads a default startup processor clock ~~selection~~ synthesis-frequency value for said phone CPU (324), and a host processor clock frequency is generated by multiplying a GPS clock that is input to a numeric controlled oscillator (NCO) that can then be digitally programmed to generate ~~any~~ a

requested output frequency ~~up to half of its input~~
frequency; and

wherein, if the GPS receiver part (302) is tracking GPS satellites and solving for frequency error, it compensates ~~such~~ a requested frequency by ~~its~~ computing of the error in said GPS oscillator (oscGPS) (312) to provide a more stable frequency to said VCO (326).

13. (Previously added) The system of claim 12, wherein:
said host CPU (324) is enabled to chose different frequencies via a communication link between the host CPU (324) and said GPS-chip (310); and

said communications transceiver part (304) can request a particular output frequency, and it can control when said VCO (326) begins outputting such frequency.

14. (Previously added) The system of claim 12, wherein:
the communications device (304) sends a request for said GPS receiver part (302) to enter said low-power mode if a low-power mode is to be engaged.

15. (Previously added) The system of claim 12, wherein:
time is maintained with a low frequency crystal with an input from osc3 (314).

16. (Previously added) The system of claim 12, wherein:
said GPS receiver part (302) sends interrupts to
the communications transceiver part (304) that wake certain
processes.

17. (Previously added) The system of claim 12, wherein:
the GPS receiver part (302) puts itself into a
sleeping, low-power mode and enables a user to decide when
to use the GPS function.

18. (Previously added) The system of claim 12, further
comprising:

a variable-VCO output from said GPS receiver part
(302) responsive to requests from said communications
transceiver part (304) to generate particular frequencies,
waveforms, and phasing.

19. (Previously added) The system of claim 12, further
comprising:

a time interval interrupt constructed from
combinations of GPS-second and GPS-millisecond interrupts
included in said GPS receiver part (302), ~~with event timing
being phased by using offsets.~~

20. (canceled.)